

# COMBO130



Mixer/Amplifier/Multimedia player

**Amplifier, mixer and tuner within the same housing**

ref 9750

- + All-in-one system
- + 5-channel mixer
- + Activate the chime via a pushbutton
- + Mountable in 19" wide racks
- + 70 V/100 V or low impedance amplified output



302

## SPECIFICATIONS

### FRONT PANEL CONTROLLERS :

- 3-channel mic volume control
- Aux1/MP3/Tuner volume control
- Aux2 volume control
- Bass/treble tone control
- MP3 reader and Tuner control
- Chime activation
- LED view meter

### REAR PANEL CONTROLLERS :

- Mute sensitivity control for priority signal

### REAR PANEL CONNECTORS :

- Mic 1 and 2 jack inputs
- RCA input for AUX1 and AUX2 channels
- RCA output to send a mixed signal to another amp
- AM/FM antenna connectors

- High-impedance loudspeaker outputs: 70 and 100 V
- Low-impedance loudspeaker outputs: 16 to 4 Ω

### TUNER:

- Save your favourite stations
- Autoscan
- Manual scan
- FM coverage : 87.00 MHz - 108.00 MHz
- Frequency hopping: 10 kHz
- Antenna : Unbalanced 75 Ω
- AM coverage : 522 kHz - 1611 kHz
- Frequency hopping : 9/10 kHz
- Antenna supplied

### USB READER:

- Reading functions
- Searching functions

- Playlist programmations
- MP3 file reading via a FAT32 formatted hard disk or USB key.

- Compatible with 500 Go devices
- 99 folders in 8 sub-directory levels
- Max sample rate: 320 kbps

### TECHNICAL SPECIFICATIONS :

- Power supply : 220 V 50-60 Hz
- Power consumption : 175 W
- Dimensions : 483(W) x 89(H) x 366(D) mm
- Net weight : 11,36 kg
- RMS power output : 130 W RMS
- Output level / Impedance: - 100 V - 70 V - 16-8 and 4 Ohms

REAR PANEL



preamp output for daisy chaining

70 V, 100 V or low-impedance power output

3 mic inputs: 1 at the front and 2 at the back

2 auxiliary inputs with adjustable volume