

marantz



SR5015

Marantz SR5015 7.2ch 8K AV receiver with HEOS Built-in and Voice Control

Just as you would expect from any Marantz AV Receiver, the SR5015 pays extra special attention to audio quality, and it creates a highly immersive and richly detailed surround sound experience. Moreover, with the latest current feedback topology and the Marantz own-developed high-definition HDAMs, the SR5015 has both the power and the finesse to astonish and astound. Stream music from leading services, and listen to music in your whole home with HEOS Built-in.

- Performance, power and connectivity to suit your audio preferences: 7.2 channel discrete power amplifier, 180W per channel.
- 8K/60Hz and 4K/120Hz pass-through support for every entertainment need: With the latest technology in HDMI support, enjoy 8K quality video from your 8K source devices or with 8K upscaling from Full HD or 4K sources.
- Support for the most advanced three-dimensional audio formats: Dolby Atmos, Dolby Atmos Height Virtualization Technology, DTS:X and DTS Virtual:X processing are all supported to allow you to listen to immersive, multi-dimensional audio.
- Enhanced Audio Return Channel (eARC) HDMI support: Through the main HDMI output, connect your TV with eARC HDMI support to allow uncompressed and object-based audio formats like Dolby Atmos and DTS:X directly from a smart TV app to your AV receiver.
- The greatest technology for home cinema: Support for the latest HDR formats including HDR10, HDR10+, HLG, Dolby Vision, 4:4:4 colour resolution and BT.2020, as well as Dynamic HDR provides exceptional picture quality for brightness, clarity and contrast.
- Advanced gaming specifications: With 4K/120Hz pass-through, Variable Refresh Rate (VRR), Auto Low Latency Mode (ALLM) and Quick Frame Transport (QFT), experience gaming thrills with amazing imaging and reduced lag.
- High-resolution streaming for audiophile approved sound: Ability to decode ALAC, FLAC and WAV lossless files up to 24-bit/192-kHz; DSD 2.8MHz and 5.6MHz tracks — enjoy your music exactly as the artist intended.
- Exclusive components elevate Marantz sonic signature: Marantz proprietary HDAM circuit boards, Current Feedback circuitry, AKM AK4458 32-bit D/A converters, and Hybrid PLL Clock Jitter Reducer produce more detailed, dynamic sound.
- Features HEOS Built-in and the free HEOS App: Your key to digital music streaming, multi-room audio and voice control throughout your entire home.
- Almost unlimited music sources: Stream from music services like Spotify Free and Premium, Amazon Music HD, Tidal and more, or stream directly from smart devices via AirPlay 2 or Bluetooth.

Modern Musical Luxury



SR5015

Technical Specs



Multichannel surround		
DTS HD Master / DTS:X / DTS:X Pro		• / • / -
DTS Neo:X / DTS Neural:X		- / •
DTS Virtual:X		-
IMAX Enhanced		-
Dolby TrueHD / Dolby Atmos / Dolby Atmos Height Virtualization		• / • / •
Dolby ProLogic Iiz / Dolby Surround		- / •
Auro 3D		-
Multichannel Stereo		•
Max Number of Processing (Preamp) Channels		7.1
Sound Enhancements		
Discrete Power Amplifier		7
Copper Plated Chassis		-
Power Transformer: Toroidal / EI		EI
Current Feedback Topology		•
Hyper Dynamic Amplifier Modules (HDAM)		•
Pure Direct		-
Gold Plated RCA Terminals		•
Clock Jitter Reducer		-
Audyssey		MultEQ XT
Audyssey Dynamic EQ / Dynamic Volume		• / •
Audyssey LFC		-
Compressed Audio Enhancer: MDAX2		•
Network		
HEOS Multi-room and Streaming		•
Bluetooth Re-transmit for Bluetooth headphones		•
Amazon Alexa / Google Voice Assistant / Apple HomePod		• / • / •
Lossy Formats: MP3 / WMA / AAC		• / • / •
Lossless Formats: FLAC HD 192/24 / WAV 192/24 / ALAC 192/24		• / • / •
DSD Audio Streaming		• (2.8/5.6MHz)
FLAC HD 192/24		•
Gapless Playback		• (FLAC, WAV, ALAC, DSD)
AirPlay Audio Streaming		• (AirPlay2)
Internet Radio		• (TuneIn)
Spotify		• (connect)
Amazon Music HD / Deezer / TIDAL / Napster / others		• / • / • / • / varies per region
Compatible with Remote APP for Smart Phones		Android / iOS
Compatible with Remote APP for Tablets		Android / iOS / Amazon Kindle
Ethernet Port		•
Wi-Fi		•
Bluetooth		•
HDMI		
HDMI Inputs: Back / Front		6 / 0
HDCP2.3 support		•
HDMI Outputs: Main / Zone		2 / -
Video Conversion Analogue -> HDMI		•
HDMI to HDMI scaling		up to 8K 60/50Hz
8K/60Hz / 4K/120Hz / CEC / eARC		• / • / • / •
Dolby Vision / HDR10+ / Dynamic HDR / HLG		• / • / • / •
ALLM (Auto Low Latency Mode) Pass-through for gaming		•
Variable Refresh Rate / Quick Frame Transport / Quick Media Switching		• / • / •
HDMI pass-through in Standby Mode		-
DSD Audio Capability		-
Auto LipSync		•
Multiroom / CI		
HEOS Multi-Room Integrated		•
TV Sound Grouping		•
Multi-Room zones		2
Zone Audio Source: HDMI / Opt, Coax / Network, USB / Analogue		• (2ch) / • (2ch) / • / •
Zone Audio Output: Speaker / Preout		• / •
Zone HDMI Output from HDMI Source		-
IP Control / RS232 Control / Web Control / App Control		• / • / • / •
IR Flasher In		•
Marantz Remote Bus		•
DC Trigger Output		1
HDMI Diagnostics		•

Others		
Auto Speaker Setup by Microphone		Audyssey MultEQ XT
FL Display		Port Hole
Graphic User Interface - GUI		Advanced
ISF Certification		•
GUI Languages		9
Setup Assistant		•
Smart Select		•
Firmware Update by Network / USB		• / •
Variable Cross Over		•
Optimized Bass Redirection		•
Bass Sync		-
ECO Mode		•
Auto Power Off		•
Sleep Timer		•
Video Inputs/Outputs		
Composite In / Out		2+1 / 1
Component In / Out		2 / 1
HDMI In / Out		6 / 2
Multi-Room Video Out: Video / HDMI		- / -
Audio Inputs/Outputs		
Analogue In / Out		4+1 / -
Phono (MM) In		•
Digital In: Optical / Coaxial		2 / 2
Multi-Room Out: Analogue / Digital		1 / -
Multichannel Pre Out		• (7.2)
Subwoofer Out		2
7.1 Multichannel Input		-
Other		
Speaker Terminal: Gold Plated Screw / Regular Screw		- / •
Number of Speaker Terminals		7
Speaker A / B		assignable
Bi-Amp Drive		assignable
Multi-Room Speaker Terminal		assignable
Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB		• / • / - / - / •
USB Audio		•
FM/AM Tuner		•
General Power		
Number of Poweramps		7
Power Output (8 ohm, 20 Hz - 20 kHz, 0.08% 2ch Drive)		100 W
Power Output (6 ohm, 1 kHz, 0.7% 2ch Drive)		140 W
Power Output (6 ohm, 1 kHz, 1% 1ch Drive)		180 W
70% Guarantee		•
General		
Metal Front Panel		-
System Remote Control		RC042SR
Pre-Programmed / Learnable / LCD Display		- / - / -
Power Consumption in W		650
Power Consumption No-Sound (ECO on / off) in W		45 W / 75 W
Standby Consumption in W		0.2
CEC Standby Consumption in W		0.5
Network Standby Consumption in W		3.7
Dimensions		
Maximum Dimensions in mm		
Antenna:Horizontal:(W x D x H)		440 x 348 x 161
Antenna:Vertical:(W x D x H)		440 x 348 x 231
w/o Antenna:(W x D x H)		440 x 338 x 161
Weight in kg		10.1
Carton Maximum Dimensions (W x D x H) in mm		520 x 429 x 243
Carton Weight (incl. product) in kg		12.3
SAP Code / EAN Black		SR5015/N1B 4951035073094
SAP Code / EAN Silver-Gold		SR5015/N1SG 4951035073100

Design and specifications are subject to change by Marantz without notice.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

www.marantz.com

Sound United
A Division of D&M Europe BV.
P.O. Box 8744
5605 LS Eindhoven
The Netherlands