



Visit product page

FOS SHOW REPLAY 1024

L005895



Show Replay and record device, Supports ArtNet and DMX, 1024 channels DMX in & out, Real-time or step-by-step record from DMX / Artnet (via Lan or WiFi), 14 Memories and each up to 20 hours can be stored in SD card.

TECHNICAL DETAILS

Features / Product description

Show Replay 1024, a usefull and versatile DMX took, with features like DMX recorder, signal booster, ArtNET to DMX node, and DMX merger.

In detail:

Supports ArtNet and DMX

- ☒ 1024 channels DMX in & out
- ☒ Real-time or step-by-step record from DMX / Artnet (via Lan or WiFi)
- ☒ 14 Memories and each up to 20 hours can be stored in SD card
- ☒ Replay can run in solo or loop mode
- ☒ Replay can run on iPad/iPhone via TouchOSC
- ☒ Bridge functions:

DMX input to DMX output (signal booster)

DMX input to Artnet output via LAN

Artnet input via LAN to DMX output

Artnet input via WiFi to DMX output


Artnet input via WiFi to Artnet out from LAN

DMX Merge (HTP/LTP/override/backup)

Technical Specifications

Default LAN IP address: 002.114.034.200
Default WiFi IP address: 002.000.000.000
DMX In: 2 x 3pin (or 5pin) XLR male
DMX Out: 2 x 3pin (or 5pin) XLR female
Power consumption: 6w max.
Power In: AC 100-240V 50-60Hz
Dimension: 482 x 200 x 44 mm
Weight: 2.0 kg

PHOTOS



www.fos-lighting.eu

