

# Product Detail Page



## MPX-44/SW

Number: 20.2420

**6-channel stereo DJ mixer,**  
with black brushed aluminium front panel.

- 6 input channels (4 stereo ways, 2 microphone ways)
- Stereo input channels, switchable 2 x phono/line and 2 x line/line, with LED level display of the stereo master
- Input channels, each with gain control and 3-way equalizer, stereo input channels with cut function
- DJ mic with automatic talkover, PAD switch and on-air switch
- Mic with PAD switch and on-air switch
- Switches illuminate blue when activated
- Adjustable, crossfader-controlled headphone output with pre-fader listening (PFL) to the stereo input channels and mic
- Replaceable crossfader with assignment switches
- Especially easy-sliding high-quality faders
- Master output with stereo LED level display
- Additional outputs booth and zone
- Connection for gooseneck light GNL-200, GNL-204 or GNL-205

## Technical Facts

<b>Mic input</b>	1.5 mV
<b>Phono input</b>	3 mV
<b>CD input</b>	150 mV
<b>Line input</b>	150 mV
<b>Master output</b>	1 V/600 Ω (master, booth, zone)
<b>Record output</b>	0.5 V/600 Ω
<b>Headphones</b>	≥ 8 Ω
<b>Frequency range</b>	20-20,000 Hz
<b>THD</b>	0.1 %
<b>S/N ratio</b>	61 dB, unweighted
<b>Equalizer, bass</b>	+12 dB, -12 dB/50 Hz (mic) +15 dB, -30 dB/50 Hz (ch. 1-4)
<b>Equalizer, midrange</b>	+12 dB, -12 dB/1 kHz (mic) +15 dB, -30 dB/1 kHz (ch. 1-4)
<b>Equalizer, treble</b>	+12 dB, -12 dB/10 kHz (mic) +15 dB, -30 dB/10 kHz (ch. 1-4)
<b>Talkover</b>	-16 dB
<b>Gooseneck light</b>	12 V/5 W, BNC
<b>Power supply</b>	230 V/50 Hz/20 VA
<b>Admiss. ambient temp.</b>	0-40 °C
<b>Dimensions</b>	482x177x105 mm, 4 RS
<b>Weight</b>	4 kg

