

## LMS-808



Number: 20.2160

### Microphone line mixer/line splitter

- Multifunctional unit with three selectable operating modes:
  - Mixer operation for mixing up to 8 mono input signals (6 x line/mic and 2 x line) to 1 stereo output
  - Line splitter operation for splitting 2 mono line inputs to 6 mono outputs
  - Level matching amplifier operation for amplifying up to 6 input signals
- 6 mono input channels, each with switchable 12V phantom power, pan control, signal/clip LED and individual selection of the operating mode
- 2 mono line input channels, each with level control and signal/clip LED

### Technical Facts Mixers

#### Line input, mono

250mV/30k $\Omega$

#### Microphone/line input

1mV/6.6k $\Omega$  (mic),

100mV/40k $\Omega$  (line)

#### Line output, stereo

1V/200 $\Omega$

#### Line output, mono

1V/200 $\Omega$

#### Frequency range

10-30,000Hz

#### THD

0.02%

#### S/N ratio

81dB, weighted

#### Crosstalk

-63dB

#### Power supply

230V~/50Hz/10VA

#### Admiss. ambient temp.

0-40 °C

#### Dimensions (WxHxD)

482x48x200mm, 1RS

#### Weight

2.9kg

#### Line input, mono

2 x XLR, bal.

#### Microphone/line input

6 x XLR, bal.

#### Line output, stereo

1 x XLR L/R, bal.

#### Line output, mono

6 x XLR, bal.

