

# Product Detail Page



## MPX-622/SW

Number: 20.2210

**6-channel stereo audio mixer,**  
especially suitable for PA and DJ applications.

- 2 mono microphone channels with talkover switch and 2-way tone control
- 4 stereo input channels, switchable phono/line (channels 1 and 2) or line/line (channels 3 and 4)
- 1 stereo master output
- 1 stereo record output, independent of the master
- 3-way equalizer with centre click for the master output and record output
- Pre-fader listening to each stereo input channel and the master output via adjustable stereo headphone output
- Switchable crossfader for crossfading between channels 1-4, any assignment possible
- Stereo LED level display



## Technical Facts

<b>Mic input</b>	1mV
<b>Phono input</b>	3mV
<b>CD input</b>	150mV
<b>Line input</b>	150mV
<b>Master output</b>	0.775V/600 $\Omega$
<b>Record output</b>	0.775V/600 $\Omega$
<b>Headphones</b>	? 8 $\Omega$
<b>Frequency range</b>	20-20,000Hz
<b>THD</b>	0.1%
<b>S/N ratio</b>	65dB
<b>Equalizer, bass</b>	$\pm$ 10dB/100Hz
<b>Equalizer, midrange</b>	$\pm$ 10dB/1kHz
<b>Equalizer, treble</b>	$\pm$ 10dB/10kHz
<b>Talkover</b>	-15dB
<b>Gooseneck light</b>	-
<b>Power supply</b>	230V~/50Hz/10VA
<b>Admiss. ambient temp.</b>	0-40 $^{\circ}$ C
<b>Dimensions</b>	482x89x95mm, 2RS
<b>Weight</b>	2.4kg