

Pioneer DJ

DDJ-FLX4

2-CHANNEL DJ CONTROLLER FOR
MULTIPLE DJ APPLICATIONS

- rekordbox and Serato compatibility
- Multi device support
- User-friendly, portable design
- Professional-style layout
- Smart Mixing features
- Seamless integration with selected streaming services
- USB audio output for microphone sound
- USB bus powered
- Performance Pads
- Class compliant (no drivers needed)

rekordbox

serato DJ Lite



LEARN TO DJ EASILY, THEN PERFORM FOR YOUR FRIENDS

2-Channel DJ controller for multiple DJ applications



SPECIFICATIONS

Software	rekordbox for PC/Mac rekordbox for iOS/Android (coming early 2023) Serato DJ Lite Serato DJ Pro
Frequency response	20 Hz – 20 kHz
S/N Ratio	103 dB
Total Harmonic Distortion	0.005 %
Input/Output Terminals	Inputs
	MIC x 1 (1/4-inch TS jack)
Bluetooth®	Outputs
	MASTER x 1 (RCA x 1) HEADPHONES x 1 (3.5-mm stereo mini jack)
USB	USB (Type C) x 2
	Wireless system
Maximum transmission distance	MASTER x 1 (RCA x 1) HEADPHONES x 1 (3.5-mm stereo mini jack)
	Frequency band
Modulation method	USB (Type C) x 2
	FH-SS (Frequency hopping spread spectrum)
Power Supply	Via USB power adapter: DC 9V, 3A Via USB bus power: DC 5V, 500 mA
Tolerable operating temperature	+5°C to +35°C (41 °F to +95°F)
Tolerable operating humidity	5% to 85% (no condensation)
Sampling rate	44.1 kHz / 48 kHz
A/D, D/A converter	16 bits / 24 bits
Input impedance	MASTER 1 kΩ or less, Headphones 10 Ω or less
Rated output level/Load impedance	MASTER 2.1 Vrms / 10kΩ
Maximum Dimensions (W x D x H)	482 x 272.8 x 59.2 mm / 18.98" x 10.74" x 2.33"
Weight	2.1 kg / 4.9 lb
Accessories	Quick Start Guide; Precautions for use; Serato flyer; USB Type-C cable; Warranty (selected regions only)

*Transmission distances are a guideline. Transmission distances may change depending on the surrounding environment.



Visit the official rekordbox website for its specifications: rekordbox.com




Visit the official Serato DJ Lite website for its specifications: serato.com

PRODUCT FEATURES

REKORDBOX AND SERATO COMPATIBILITY

Use rekordbox or Serato DJ Lite for free by connecting your PC/Mac to the DDJ-FLX4. And if you want to upgrade to Serato DJ Pro, you can buy a license or subscription.




BRAND-NEW SMART MIXING FEATURES

Smart Fader automatically adjusts the volume, bass volume, and BPM of the music so you can smoothly transition from one track to the next by simply moving the channel faders or crossfader. And Smart CFX applies a combination of effects with a turn of one knob to add drama to the sound.

MULTI-DEVICE SUPPORT

Connect a PC or Mac to the DDJ-FLX4. And, if you use it with rekordbox for iOS/Android when the update becomes available in early 2023, you'll be able to connect to your iPhone, iPad, or an Android phone or tablet via Bluetooth® or a USB cable.




SEAMLESS INTEGRATION WITH SELECTED STREAMING SERVICES

rekordbox is compatible with the TIDAL, Beatport Streaming, Beatsource Streaming, and SoundCloud Go+ platforms (subscriptions required), so you can choose from millions of tracks and mix them together on the DDJ-FLX4.

USER-FRIENDLY, PORTABLE DESIGN

The layout of the controls on the DDJ-FLX4 makes it easy to learn to DJ and is inherited from professional Pioneer DJ products. Everything is simple to use and neatly arranged, so the controller is compact enough to take anywhere you want to practice or perform.



USB AUDIO OUTPUT FOR MICROPHONE SOUND

The DDJ-FLX4 blends the audio from the microphone with the music you're playing, so there's no need for an external mixer or soundcard – making the controller ideal for live-streaming.

* Disclaimer: Specifications and price are subject to change. | * Pioneer DJ is a trademark of PIONEER CORPORATION and is used under license. | * rekordbox™ is a trademark or registered trademark of AlphaTheta Corporation. | * Serato DJ Lite and Serato DJ Pro is a registered trademark of Serato Limited. | * Beatport and its logo is a trade name or registered trademark of Beatport, LLC. | * SoundCloud and the SoundCloud logo are registered trademarks of SoundCloud Ltd. | * TIDAL is a trademark of TIDAL MUSIC AS. | * iPhone, iPad, iPod touch, iTunes, Mac and Mac OS are registered trademarks of Apple Inc. in the U.S. and other countries. | * iOS is a trademark containing Cisco trademark signs in the U.S. and other countries. | * Android is a trademark of Google LLC. | * The Bluetooth® word mark and logos are registered trademarks owned by the Bluetooth SIG, Inc. and any use of such marks by AlphaTheta Corporation is under license. Other trademarks and trade names are those of their respective owners. | * Other product, technology, and company names, etc. mentioned herein are trademarks or registered trademarks of their respective owners.

