

COMBO60



Mixer/Amplifier/Multimedia player

All-in-one, ultra compact and super efficient

ref 9749

- + Compact all-in-one system
- + Built-in USB player and Tuner
- + 2 Line inputs and one Mic input
- + Music on hold and telepaging functions
- + Safety priority output
- + 3-band equalizer



SPECIFICATIONS

FRONT PANEL CONTROLLERS :

- 2-channel mic volume control
- Aux1/MP3/Tuner volume control
- Master volume control
- Bass/medium/treble tone control
- MP3 reader and Tuner control
- USB port for Mass storage reader

REAR PANEL CONTROLLERS :

- Music on-hold volume settings
- Public announcements volume settings
- Aux / CD/MP3/Tuner front volume controller

REAR PANEL CONNECTORS :

- AUX input via RCA connector
- CD input via RCA connector
- 3-pin telephone paging input connector

- Music on-hold 4-pin input connector
- Manual priority input terminal
- High-impedance loudspeaker outputs: 100 V
- Low-impedance loudspeaker outputs: 4, 8, 16 Ω

TUNER :

- Save your favourite stations
- Autoscans
- Manual scan
- FM coverage : 87.00 MHz - 108.00 MHz
- Frequency hopping: 10 kHz
- Antenna : Unbalanced 75 Ω
- AM coverage : 522 kHz - 1611 kHz
- Frequency hopping : 9/10 kHz
- Antenna supplied

USB READER:

- Reading functions
 - Searching functions
 - Playlist programmations
 - MP3 file reading via a FAT32 formatted hard disk or USB key.
 - Compatible with 500 Go devices
 - 99 folders in 8 sub-directory levels
 - Max sample rate: 320 kbps
- ### TECHNICAL SPECIFICATIONS :
- Power supply : 230 V - 50 Hz
 - Dimensions L x W x H : 90 x 270 x 260 mm
 - Weight : 5 kg
 - RMS power output : 60 W RMS
 - Output level / Impedance : - 100 V - 16-8 et 4 Ohms

Priority and speaker 100 V/4-16 Ohms outputs

REAR PANEL



2 line inputs/1mic input

Telephone paging and music on-hold functions