



# MOJO500Liberty

Column system on battery with mixer, Reverb and Bluetooth

Code : H10899

EAN : 3662009019574

## Technical data

### COLOMN

- Power 100W RMS - 200W max
- Frequency response 180Hz -20KHz
- Sensitivity(1W@1m) 92 dB
- Max. SPL (@1m) 116 dB
- Nominal impedance 4 Ohms
- Boomer 6 X 2.75"
- Dispersion 120° x 20° (HxV)
- Connector Slot-in inegrated into the base
- Dimensions 80 x 80 x 830 mm x2
- Net weight 2,45 kg + 1,20 kg = 3,65 kg

### SUBWOOFER

- Power 150W RMS - 300W max
- Frequency response 50 - 200Hz
- Sensitivity(1W@1m) 92 dB
- Max. SPL (@1m) 116 dB
- Boomer 8"
- Dimensions 340 x 430 x 400 mm
- Net weight 10.8 kg

### AMPLIFICATION

- Low frequencies 1 x 150W RMS / Classe D - 8 Ohms
- Mid/High frequencies 1 x 100W RMS / classe D - 4 Ohms
- Inputs:
  - CH1/CH2 : - 1 x Combo XLR/Jack Ligne/Micro/Guitar
  - CH3/4/5/6 : 1 x Jack Guitare/Line
  - CH7/8 : 1 x RCA L/R ligne + 1 x Jack 3,5 stereo Aux + Bluetooth®
- Outputs:
  - 1 Slot-in on the top of the subwoofer
  - 1x XLR balanced for the link with another system
- High, Mid and High: Frequencies equalizer for 1 to 6 channels
- Level : Volume settings for each channel
- Reverb: Activating and adjusting the reverb on channels 1 to 6
- Master: Volume Setting the general level
- Pair: Enabling Bluetooth pairing
- Battery Level: Battery level indication
- Battery life
  - Charging time : 4 hours
  - Discharge time (limiter): 5 hours
  - Discharge time at 80% of power: 8 hours
  - Discharge time in background music: 15 hours