

Product

Document download

Convert the signal from DMX-512 to 72 CH. ANALOGUE output.

- Convert the signal from MIDI to 72 CH.

ANALOGUE output.

- The front panel alpha-numeric display shows the DMX start address and programming options.
- The last scene remains when DMX disappears.
- Pre-store a scene and is available for emergency.
- Memory backup with EEPROM.
- CHASE function can be selected from 1 to 72 channel & speed control.
- Select ANALOGUE output from +(-)10V, +(-)12V and +(-)15V.
- Receive NOTE ON/OFF signal of MIDI.

Specifications

Voltage: 230V

Dimensions: 483 x 130 x 45 mm (LxWxH)

Weight: 1,65 kg