

Product Detail Page



PA-302

Number: 17.1270

Mono PA mixing amplifier,
20W_{MAX}.

- 1 microphone input, 1 aux input
- 2 speaker outputs, switchable
- Built-in speaker
- Can also be operated as an intercom system
- Siren and fog horn, automatic fog horn
- Supplied with hand-held microphone
- 12/24V battery operation, automatic switching

Technical Facts

Output power	14W _{RMS} , 20W _{MAX}
Mic input	3mV
Aux input	50mV
Output	4-16Ω
Frequency range	20-20,000Hz
S/N ratio	65dB
THD	< 0.5%
Power supply	12-15V = /2A, 24V = /1A
Admiss. ambient temp.	0-40 °C
Dimensions	175x60x170mm
Weight	1.5kg
Inputs	
Mic	1 x 6.3mm jack
Aux	1 x RCA
Outputs	
Speakers	2 x 2-pole screw plug-in terminal
Ext. speaker	1 x 3-pole screw plug-in terminal with jumper
Power supply	1 x 2-pole screw plug-in terminal